

N-Channel Enhancement Mode Field Effect Transistor

Product Summary



- V_{DS} 60V
- I_D (Silicon limited) 150A
- $R_{DS(ON)}$ (at $V_{GS}=10V$) <3.5 mohm
- $R_{DS(ON)}$ (at $V_{GS}=4.5V$) <5.0 mohm
- 100% EAS Tested
- 100% ∇V_{DS} Tested
- ESD Protected up to 2.0KV(HBM)

General Description


- Split Gate Trench MOSFET technology
- Excellent package for heat dissipation
- High density cell design for low $R_{DS(ON)}$
- Moisture Sensitivity Level 1
- Epoxy Meets UL 94 V-0 Flammability Rating
- Halogen Free

Applications

- Synchronous Rectification
- Battery Protection Circuit
- Motor drivers and Uninterruptible Power Supplies



TO-263



■ Absolute Maximum Ratings ($T_A=25^\circ\text{C}$ unless otherwise noted)

Parameter	Symbol	Limit	Unit
Drain-source Voltage	V_{DS}	60	V
Gate-source Voltage	V_{GS}	± 20	V
Drain Current (Silicon limited)	I_D	$T_A=25^\circ\text{C}$	18
		$T_A=100^\circ\text{C}$	11
		$T_C=25^\circ\text{C}$	150
		$T_C=100^\circ\text{C}$	95
Pulsed Drain Current ^A	I_{DM}	450	A
Avalanche energy ^B	EAS	441	mJ
Total Power Dissipation ^C	P_D	$T_A=25^\circ\text{C}$	2
		$T_A=100^\circ\text{C}$	0.8
		$T_C=25^\circ\text{C}$	147
		$T_C=100^\circ\text{C}$	59
Junction and Storage Temperature Range	T_J, T_{STG}	-55~+150	$^\circ\text{C}$

■ Thermal resistance

Parameter	Symbol	Typ	Max	Units
Thermal Resistance Junction-to-Ambient ^D	$R_{\theta JA}$	12	15	$^\circ\text{C/W}$
Thermal Resistance Junction-to-Ambient ^D		Steady-State	48	
Thermal Resistance Junction-to-Case	$R_{\theta JC}$	0.7	0.85	

■ Ordering Information (Example)

PREFERRED P/N	PACKING CODE	Marking	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
YJB150G06AK	F2	YJB150G06AK	800	/	8000	13" reel



YJB150G06AK

■ Electrical Characteristics (T_j=25°C unless otherwise noted)

Parameter	Symbol	Conditions	Min	Typ	Max	Units
Static Parameter						
Drain-Source Breakdown Voltage	BV _{DSS}	V _{GS} = 0V, I _D =250μA	60			V
Zero Gate Voltage Drain Current	I _{DSS}	V _{DS} =60, V _{GS} =0V			1	μA
		V _{DS} =60, V _{GS} =0V, T _j =150°C			100	
Gate-Body Leakage Current	I _{GSS}	V _{GS} = ±20V, V _{DS} =0V			±10	μA
Gate Threshold Voltage	V _{GS(th)}	V _{DS} = V _{GS} , I _D =250μA	1.0	1.7	2.5	V
Static Drain-Source On-Resistance	R _{DS(on)}	V _{GS} = 10V, I _D =20A		2.7	3.5	mΩ
		V _{GS} = 4.5V, I _D =20A		3.5	4.8	mΩ
Diode Forward Voltage	V _{SD}	I _S =20A, V _{GS} =0V		0.8	1.3	V
Maximum Body-Diode Continuous Current	I _S				150	A
Gate resistance	R _G	f= 1 MHz		2.0		Ω
Dynamic Parameters						
Input Capacitance	C _{iss}	V _{DS} =30V, V _{GS} =0V, f=1MHZ		4650		pF
Output Capacitance	C _{oss}			850		
Reverse Transfer Capacitance	C _{rss}			65		
Switching Parameters						
Total Gate Charge	Q _g	V _{GS} =10V, V _{DS} =30V, I _D =25A		71		nC
Gate-Source Charge	Q _{gs}			17		
Gate-Drain Charge	Q _{gd}			10.5		
Reverse Recovery Charge	Q _{rr}	I _r =20A, di/dt=500A/us		39.8		ns
Reverse Recovery Time	t _{rr}			41.6		
Turn-on Delay Time	t _{D(on)}	V _{GS} =10V, V _{DD} =30V, I _D =25A R _{GEN} =2Ω		15.9		ns
Turn-on Rise Time	t _r			55.2		
Turn-off Delay Time	t _{D(off)}			57.5		
Turn-off fall Time	t _f			91.3		

A. Repetitive rating; pulse width limited by max. junction temperature.

B. V_{DD}=50V, R_G=25Ω, L=0.5mH, I_{AS}=42A.

C. P_d is based on max. junction temperature, using junction-case thermal resistance.

D. The value of R_{θJA} is measured with the device mounted on 1in2 FR-4 board with 2oz. Copper, in a still air environment with T_A =25°C. The Power dissipation P_{DSM} is based on R_{θJA} ≤ 10s and the maximum allowed junction temperature of 150°C. The value in any given application depends on the user's specific board design.



■ Typical Performance Characteristics




Figure1. Output Characteristics




Figure2. Transfer Characteristics




Figure3. Capacitance Characteristics




Figure4. Gate Charge




Figure5. On-Resistance vs. Drain Current and Gate Voltage




Figure6. Normalized On-Resistance



YJB150G06AK




Figure 7. On-Resistance vs Gate to Source Voltage




Figure 8. Forward characteristics of reverse diode




Figure 9. Normalized breakdown voltage




Figure 10. Normalized Threshold voltage




Figure 11. Current dissipation




Figure 12. Power dissipation



YJB150G06AK




Figure13. Normalized Maximum Transient thermal impedance





Figure14. Safe Operation Area



YJB150G06AK

■ TO-263-HY Package information



SYMBOL	DIMENSIONS					
	INCHES			Millimeter		
	MIN.	NDM.	MAX.	MIN.	NDM.	MAX.
A1	0.000	---	0.010	0.000	---	0.250
A2	0.174	0.180	0.186	4.430	4.580	4.730
b	0.028	0.032	0.036	0.720	0.820	0.920
b2	0.046	0.050	0.054	1.180	1.280	1.380
c	0.013	0.015	0.018	0.330	0.390	0.450
c2	0.048	0.050	0.053	1.220	1.280	1.340
D	0.394	0.400	0.406	10.000	10.150	10.300
D1	0.295	0.307	0.319	7.500	7.800	8.100
D2	0.303	0.315	0.327	7.700	8.000	8.300
E	0.571	0.591	0.610	14.500	15.000	15.500
E1	0.337	0.341	0.348	8.550	8.700	8.850
E2	0.276	0.287	0.299	7.000	7.300	7.600
e	0.200BSC			5.080BSC		
L	0.070	---	0.110	1.790	---	2.790
L1	0.044	---	0.056	1.120	---	1.420
L2	0.030	---	0.070	0.770	---	1.770
L3	0.197REF			5.000REF		
θ	0°	---	8°	0°	---	8°

NOTE:

1. PACKAGE BODY SIZES EXCLUDE MOLD FLASH AND GATE BURRS.
2. TOLERANCE 0.1mm UNLESS OTHERWISE SPECIFIED.
3. THE PAD LAYOUT IS FOR REFERENCE PURPOSES ONLY.



YJB150G06AK

Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.